

Release Letter

Product:	<i>DIVAR IP 5000 Family</i>
Version:	<i>Software version 03.80.0033</i>

This letter contains latest information about the above mentioned Bosch DIVAR IP 5000 Family software version.

1. General

DIVAR IP 5000 is an affordable, easy to use all-in-one recording management solution for network surveillance systems of up to 32 channels (all channels pre-licensed).

Running the full Bosch recording solution including the Video Streaming Gateway to integrate 3rd party cameras, DIVAR IP 5000 is an intelligent IP storage device that provides both, a professional video recording solution and ease of operation.

DIVAR IP 5000 is a 4-bay mini tower unit that combines simple web-based management and state-of-the-art recording management into a single cost-effective, plug and play IP recording appliance for IT-minded customers which are seeking for a state-of-the-art “second generation” DVR and NVR recording solution.

- The system comes with the following network settings
 - Default
 - IP Settings: automatically obtained from DHCP server
 - Computer name: mydivar
 - Fallback
 - IP Address: 192.168.0.200
 - Subnet mask: 255.255.255.0
 - Remote access
 - Port of web interface / recording system: 80 (http), 443 (https)
 - Support of Bosch Remote Portal
 - Supported DDNS services: dyndns.org, no-ip.com, selfhost.com
- Initial installation
 - The system is designed for remote operation and web based configuration. No monitor, mouse and keyboard need to be used. Only network and power connection is required for setup and operation.
 - Configuration Wizard can be accessed via the following URL: <http://mydivar>
 - The IP Helper application can be used as a fallback option for network configuration. It can be obtained from <http://mydivar.com>

2. New subcomponent software versions

- DIVAR IP software 3.80.0033
 - CameraFirmwareFile 06.43.01.19
 - DiskManagementService 03.62.14
 - MpegActiveX 6.13.00.84
 - TranscoderService 06.44.00.22
 - VRM 03.80.00.33
 - VSG 06.44.00.22

3. Changes

New Features

- Device Replacement:
It is possible to replace an IP device of the same model (camera or encoder) and inherited the settings of the old IP device without losing the video recording history of the previous IP device. This can be done via the web interface of the DIP 5000.
- Recording Encryption:
All video, audio and meta data stored on the DIP 5000 can be recorded in an encrypted way. So the video, audio and meta data content cannot be replayed by a non authorized user. The replay can be done via the web interface of the DIP 5000 and also via the Bosch Video Security Client and the Bosch Video Security App.
- Audio back channel now available to talk back to a loudspeaker connected to an IP device (camera or encoder). This feature is supported at Bosch Video Security App (iOS 2.3) and Bosch Video Security Client (Windows 2.2)
- Full H.265 support:
H.265 cameras can be now transcoded as well.
- Motion Recording for Sony Cameras (7th generation):
Now it is possible to record Sony cameras based on motion alarm. Precondition is to configure the motion detector of the Sony camera directly at the web interface of the camera. Motion events will be send as ONVIF events.

Remarks

- Upload is only possible via Chrome or Firefox due to the fact of the files size >6GB
- During upgrade process the DIP 5000 might reboot several times

Bugfixes

- Corrected display and replay of recorded clips in continuous and alarm recording
- Security Updates and latest Windows updates.

4. Restrictions and known issues

- General:
 - Upload is only possible via Chrome or Firefox due to the fact of the files size >6GB
 - During upgrade process the DIP 5000 might reboot several times
- Supported devices
 - Bosch IP video devices with FW \geq 5.73
 - Exception: NBC-255-W and NBC-265-W not supported
 - Megapixel and Ultra HD devices: see transcoder restrictions
 - 3rd party cameras: see 3rd party camera restrictions
 - Some advanced configuration through Configuration Manager or camera-webpages are locked as long as the initial configuration has been done through DIVAR IP webpages
 - Support for moving cameras is limited on DIVAR IP webpage (no positioning of field of view available in webpages)
- 3rd party camera restrictions
 - No support for event-based recording (only for Sony cameras)
 - TCP protocol only
 - Configuration interface of 3rd party vendor needs to be used to set up network, stream and access settings
 - VCA meta-data is not recorded
- Transcoder restrictions
 - Maximum transcoder source stream resolution is 1920x1080p30
 - Source stream needs to be compressed in h264
- Storage restriction
 - The system needs to be powered down before mounting / changing hard drives

5. Installation Notes

This software is available as an online update for the products listed above. The update can be applied via Configuration Wizard or Device Monitor, if the system is connected to the internet.

Supported browsers are Internet Explorer 10, Internet Explorer 11, Microsoft Edge Firefox 43, Chrome 48. For firmware upgrade we recommend Firefox and Chrome, big update files are not supported by IE 10, 11 and Microsoft Edge.