

DS7443S LED Keypad

www.boschsecurity.com



BOSCH
Invented for life



- ▶ Programmable keys
- ▶ Simple installation

The DS7443S Keypad is a four-wire light-emitting diode (LED) keypad with six zone LEDs. It has three programmable emergency keys for fire, special emergency, and panic.

Functions

Programmable Keys

One key is pre-set as a fire emergency key. The other two keys can be programmed as a special emergency key and a panic key. Adhesive labels are provided.

Simple Installation

Surface mount the keypad directly to an interior wall or to a single gang box.

Certifications and approvals

Region	Certification
Europe	CE 1999/5/EC, EN60950 Dec 1992 (2nd edition) +A1: 1992 +A2: 1993, EN50081-1: 1992, EN50082-1: 1992
Belgium	INCERT B-509-0004/b
USA	UL DS7443S: AMCX: Central Station Alarm Units (UL1610, UL1635), AOTX: Local Alarm Units (UL464, UL609), APAW: Police Station Alarm Units (UL365, UL464), APOU: Proprietary Alarm Units

Region	Certification
	(UL1076), NBSX: Household Burglar Alarm System Units (UL1023), UOXX: Control Unit Accessories, System (UL864), UOTU: Control Units and Accessories - Household System Type (UL985)

Installation/configuration notes

Compatibility Information

Control Panels DS7400Xi, DS7080iP-32, and DS7060

Wiring Considerations

The recommended wiring from the control station to the control panel is 0.8 mm (22 AWG), unshielded four-wire cable. Only one control station can be on any wire run. Refer to the control panel's installation manual for information on total number of control stations allowed and maximum wire run length.



Notice

Control station wiring cannot be shared with multiplex, options bus, telephone, or siren wiring.

Technical specifications

Product Characteristics

Dimensions:	13 cm x 8 cm x 4 cm (5 in. x 3.25 in. x 0.25 in.)
-------------	--

Power Requirements

Current Draw:	80 mA standby; 100 mA alarm
---------------	-----------------------------

Ordering information

DS7443S LED Keypad

Provides six zone LEDs and three programmable emergency keys.

Order number **DS7443S**

DS7443S-ITA LED Keypad

For use in Italy. Provides six zone LEDs and three programmable emergency keys.

Order number **DS7443S-ITA**

DS7443S-BEL LED Keypad

For use in Belgium. Provides six zone LEDs and three programmable emergency keys.

Order number **DS7443S-BEL**

DS7443S-SWE LED Keypad

For use in Sweden. Provides six zone LEDs and three programmable emergency keys.

Order number **DS7443S-SWE**

Represented by:

Americas:

Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:

Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:

Bosch (Shanghai) Security Systems Ltd.
201 Building, No. 333 Fuquan Road
North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

America Latina:

Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
latam.boschsecurity@bosch.com
www.boschsecurity.com