

# E70 Multi-candela, Wall-mount, Low-profile Speaker Strobes

www.boschsecurity.com



**BOSCH**  
Invented for life



- ▶ 24 VDC, filtered or unfiltered
- ▶ Field-selectable candela settings (15 cd, 30 cd, 75 cd or 110 cd)
- ▶ ADA, NFPA, ANSI compliant
- ▶ Compatible with SM and DSM Synchronization Modules
- ▶ Low average current draw

The E70 Multi-candela Speaker Strobes provide high audio output with clear audibility, and four field-selectable light intensity settings (15 cd, 30 cd, 75 cd or 110 cd). They are designed to meet the critical needs of the life safety industry for effective emergency voice communications, tone signaling and visible signaling to alert the hearing impaired. These notification appliances provide a way to alert hearing impaired persons of an alarm condition, and are well-suited for areas of public gathering such as stores, schools, hospitals, nursing homes and offices. A speaker mounting plate with a built-in level adjustment allows for a faster and easier installation. The two-screw grill cover creates an attractive appearance.

The high-efficiency speakers are designed for maximum output at a minimum wattage across a frequency range of 400 Hz to 4 kHz.

When used with the SM (single) or DSM (dual) Synchronization Modules, the strobe produces a synchronized flash for compliance with ADA guidelines concerning photosensitive epilepsy. All strobe input is

compatible with standard reverse polarity type supervision of circuit wiring by a fire alarm control panel (FACP).

## Certifications and approvals

Cooper Wheelock, Inc. holds these Listings and Approvals:

Region	Certification	
USA	UL	UUKC: Signaling Appliances and Equipment for the Hearing Impaired (UL1971), UUMW: Speakers and Amplifiers for Fire Protective Signaling Systems (UL1480, UL1711, and UL2043)
	CSFM	see our website

## Installation/configuration notes

### Compatible Products

The following products are compatible with the E70 Speaker Strobes:

Category	Product ID	Product Description
Control Panels	D7022 <sup>1</sup>	Conventional FACP
	D7024 <sup>2</sup>	Addressable FACP
	D7024	Conventional FACP
	D8024 <sup>1</sup>	Analog FACP
	D9124 <sup>1</sup>	Addressable FACP
	D10024A <sup>1</sup>	Analog FACP
	FPD-7024 <sup>2</sup>	Addressable FACP
	FPD-7024	Conventional FACP
Modules	FPA-1000	Analog Addressable FACP
	SM-12/24-R	Synchronization module (red)
	DSM-12/24-R	Dual synchronization module (red)

These speakers are compatible with Wheelock SAFEPATH4 Facility Communication Systems and Bosch Voice Evacuation Systems.

<sup>1</sup> For synchronization, use the SM or DSM modules with these control panels. The synchronization module must be set for 24 V operation. When used, the D7022 must be set for 24 VDC operation.

<sup>2</sup> When used with a D7039 Multiplex Expansion Module, the D7024 and FPD-7024 become addressable fire alarm control panels (FACPs).

### Mounting

The low profile design of these notification appliances creates more wiring space in standard electrical back boxes. The speaker mounting plate incorporates a built-in level adjustment feature allowing for a faster and easier installation.

These speaker strobes wall mount on the indicated back boxes for the indicated applications:

	Conduit Applications	Surface Mounted	Flush Mounted
Four-inch square*			•
SBB Back Box	•	•	

\* Requires an SER extension ring.

### Wiring



#### Notice

Do not use the strobe unit in coded or pulsed signaling circuits.

The input terminals accept wires with diameters between 18 AWG and 12 AWG (ISO 0.75 mm<sup>2</sup> and 4 mm<sup>2</sup>).

### Parts included

Quant.	Component
1	Speaker Strobe

1	Mounting Plate
1	Hardware pack
1	Literature pack

### Technical specifications

#### Electrical

##### Strobe Current (RMS maximum)

VDC: 15 cd = 60 mA; 30 cd = 92 mA; 75 cd = 165 mA; 110 cd = 220 mA

VFWR: 15 cd = 102 mA; 30 cd = 155 mA; 75 cd = 253 mA; 110 cd = 347 mA

##### Voltage (input)

Nominal: 24 VDC

Range: 16 VDC or FWR to 33 VDC or FWR

#### Environmental

Relative Humidity: Up to 85%, non-condensing

Temperature (Operating): +32°F to +120°F (0° to +49°C)

#### Mechanical

Dimensions (H x W x D): 5.1 in. x 5.1 in. x 5.2 in. (13.0 cm x 13.0 cm x 13.3 cm)

Material: Molded plastic enclosure incorporating a Xenon flashtube and Lexan lens.

Candela Selections: 15 cd, 30 cd, 75 cd, or 110 cd

#### Speaker Volume at 10 ft (3 m)

0.125 (1/8) W: 77.5 dBA

0.25 (1/4) W: 80.4 dBA

0.5 (1/2) W: 83.2 dBA

1 W: 85.7 dBA

2 W: 87.8 dBA

#### Trademarks

All hardware and software product names used in this document are likely to be registered trademarks and must be treated accordingly.

### Ordering information

#### E70-24MCW-FN Low-Profile Speaker Strobe (nickel)

Nickel finish, 24 VDC device with high-efficiency sound output, dual voltage capability (25 VRMS or 70 VRMS), field-selectable taps from 1/8 W to 2 W, and strobe intensities of 15 cd, 30 cd, 75 cd, or 110 cd

Order number **E70-24MCW-FN**

**E70-24MCW-FR Low-Profile Speaker Strobe (red)**

Red, 24 VDC device with high-efficiency sound output, dual voltage capability (25 VRMS or 70 VRMS), field-selectable taps from 1/8 W to 2 W, and strobe intensities of 15 cd, 30 cd, 75 cd, or 110 cd  
Order number **E70-24MCW-FR**

**E70-24MCW-FW Low-Profile Speaker Strobe (white)**

White, 24 VDC device with high-efficiency sound output, dual voltage capability (25 VRMS or 70 VRMS), field-selectable taps from 1/8 W to 2 W, and strobe intensities of 15 cd, 30 cd, 75 cd, or 110 cd  
Order number **E70-24MCW-FW**

**Accessories**

**ISP2-R Surface Adapter (red)**

13.3 cm (5.25 in.) square, 3 cm (1.1875 in.) deep  
Order number **ISP2-R**

**ISP2-W Surface Adapter (white)**

13.3 cm (5.25 in.) square, 3 cm (1.1875 in.) deep  
Order number **ISP2-W**

**RP-R Retrofit Plate (red)**

20.3 cm (8 in.) high, 14.9 cm (5.875 in.) wide.  
**Not Available.**  
Order number **RP-R**

**SBB-R Surface-mount Back Box (red)**

14 cm (5.5 in.) x 14.2 cm (5.6 in.) x 9.1 cm (3.6 in.)  
Order number **SBB-R**

**SBB-W Surface-mount Back Box (white)**

14 cm (5.5 in.) x 14.2 cm (5.6 in.) x 9.1 cm (3.6 in.)  
Order number **SBB-W**

**SER-R Square Semi-flush Extension Ring (red)**

12.7 cm (5 in.) square by 4 cm (1.5625 in.) deep  
Order number **SER-R**

**SER-W Square Semi-flush Extension Ring (white)**

12.7 cm (5 in.) square by 4 cm (1.5625 in.) deep  
Order number **SER-W**

**SFP-R Semi-flush Plate (red)**

15.2 cm (6 in.) square by 0.8 cm (0.3125 in.) thick  
Order number **SFP-R**

**Represented by:**

**Americas:**

Bosch Security Systems, Inc.  
130 Perinton Parkway  
Fairport, New York, 14450, USA  
Phone: +1 800 289 0096  
Fax: +1 585 223 9180  
security.sales@us.bosch.com  
www.boschsecurity.us

**Europe, Middle East, Africa:**

Bosch Security Systems B.V.  
P.O. Box 80002  
5617 BA Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
Fax: +31 40 2577 330  
emea.securitysystems@bosch.com  
www.boschsecurity.com

**Asia-Pacific:**

Robert Bosch (SEA) Pte Ltd, Security Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2808  
Fax: +65 6571 2699  
apr.securitysystems@bosch.com  
www.boschsecurity.asia

**China:**

Bosch (Shanghai) Security Systems Ltd.  
201 Building, No. 333 Fuquan Road  
North IBP  
Changning District, Shanghai  
200335 China  
Phone +86 21 22181111  
Fax: +86 21 22182398  
www.boschsecurity.com.cn

**America Latina:**

Robert Bosch Ltda Security Systems Division  
Via Anhanguera, Km 98  
CEP 13065-900  
Campinas, Sao Paulo, Brazil  
Phone: +55 19 2103 2860  
Fax: +55 19 2103 2862  
latam.boschsecurity@bosch.com  
www.boschsecurity.com