

Compatible UL Listed Fire Alarm Control Panels



Bosch Security Systems, Inc. makes no claim either written, verbal, or implied that any specific, individual FACP will work with the C900V2 Network Dialer Capture Module. Per NFPA Standard 72 requirements, communications from each and every actuating device must be successfully tested from the actuating device to the fire alarm supervising station at the time of installation, and after any change in the configuration of the FACP.

The UL Listed Fire Alarm Control Panels (FACPs) listed in *Table 1* on page 2, are proven to be compatible with the C900V2 Network Dialer Capture Module and the D6600 Receiver/Gateway under the method required by Underwriters Laboratories (UL).

FACPs that are not UL Listed as compatible should not be used with the C900V2. Adding UL Listed FACPs to this list is easy for Bosch Security Systems to do. If the FACP you wish to use with the C900V2 is not in *Table 1*, contact Technical Support at (800) 289-0096.

C900V2

Manufacturer	Compatible UL Listed Control Panel & Digital Alarm Control Transmitters (DACT)	C900V2 Compatible Control Panel Formats										
		Radionics Modem			Radionics BFSK		SIA Bell 103, 110 & 300 baud	Pulse		DTMF		
		II	Ile	IIIa ²	2300Hz z ACK	1400Hz ACK		2300Hz	1400Hz	Contact ID	Ademco 4/2 Express	Ademco High Speed
Bosch / Radionics	D2071 DACT ⁸				X			X				
	D7024 ⁸			X	X	X	X			X		
	D7212 ⁸			X	X	X						
	D7212B1 ⁸		X		X	X						
	D7412 ⁸			X	X	X						
	D7412G ⁸			X	X	X						
	D8112 ⁸	X			X	X		X	X			
	D9068 DACT ⁸			X			X		X	X		
	D9112 ⁸			X	X	X						
	D9112B1 ⁸		X		X	X						
	D9124* ⁸		X	X								
	D9412 ⁸			X	X	X						
D9412G ⁸			X	X	X							
Bosch / Detection Systems	DS7400Xi ⁸				X	X	X	X	X	X		
	DS9400M & i ⁸				X	X	X	X	X	X		
	DS9471 ⁸				X			X				
	DS9602 DACT ⁸							X	X	X		
ADT	Focus 200 Plus ⁸									X		
Honeywell	VISTA50P									X		
	VISTA128B									X		
	VISTA250BP									X		
GE Security (EST)	EST-3									X		
	Quickstart (QS4)									X		

* when D9112LTB is used, Modem Ile format
 when D9112LTB-EX or D9412GLTB is used, Modem IIIa²

⁸ Tested to UL 8TH Edition

Table 1: C900V2 Compatible UL Listed Fire Alarm Control Panels (FACPs)

Manufacturer	Compatible UL Listed Control Panel & Digital Alarm Control Transmitters (DACT)	C900V2 Compatible Control Panel Formats										
		Radionics Modem			Radionics BFSK		SIA Bell 103, 110 & 300 baud	Pulse		DTMF		
		II	Ile	IIIa ²	2300Hz z ACK	1400Hz ACK		2300Hz	1400Hz	Contact ID	Ademco 4/2 Express	Ademco High Speed
Simplex	4005 w/9810				X	X	X	X	X			
	4006				X	X	X	X	X	X		
	4008				X	X	X	X	X	X		
	4010 w/9810				X	X	X	X	X			
	4010 w/9816				X	X	X	X	X	X		
	4100 w/6052				X	X	X	X	X	X		
Notifier	AFP400 v3.52 w/UDAC ⁸									X		
	NFW2-100 9200UD v3.1 ⁸									X		
	AIM-200 w/UDAC ⁸									X		
	NFS-640 w/ Built-in DACT ⁸									X		
Siemens	MXL - W/MDACT ⁸									X		
	FireFinder XLS PMI v7.11						X			X		
Hochiki	FireNET 4127 (v4.00H) w/FN-DACT						X			X		
	Hochiki FireNET PLUS 1127 (v07.0039)						X			X		

* when D9112LTB is used, Modem Ile format
 when D9112LTB-EX or D9412GLTB is used, Modem IIIa²
⁸ Tested to UL 8TH Edition

Table 1 (continued): C900V2 Compatible UL Listed Fire Alarm Control Panels (FACPs)

C900V2

Manufacturer	Compatible UL Listed Control Panel & Digital Alarm Control Transmitters (DACT)	C900V2 Compatible Control Panel Formats										
		Radionics Modem			Radionics BFSK		SIA Bell 103, 110 & 300 baud	Pulse		DTMF		
		II	Ile	IIIa ²	2300Hz z ACK	1400Hz ACK		2300Hz	1400Hz	Contact ID	Ademco 4/2 Express	Ademco High Speed
Silent Knight	SK5207 ⁸				X	X	X		X			
	IFP-1000 ⁸									X		
	IFP-1000, Rev 9 or higher						X					
	IFP-2000, Rev 3 or higher						X					
	SK5820 ⁸									X		
	SK-5128									X		
	SK-5820XL									X		
	SK-5104								X			
	SK-5208									X		
UTC	SA-DACT									X		
	F-DACT								X	X		
	2-DACT									X		
	VM-DACT									X		
Vigilant	VS1-RD									X		
Firelite	411-UDAC									X		
	MS-9050UD Ver 03.2 B1 Rev2							X	X	X		
	MS-9200UDLS Ver 05.3 B1 Rev3						X (SIA8 / SIA20)			X		
	MS-9600ULDS									X		

* when D9112LTB is used, Modem Ile format
 when D9112LTB-EX or D9412GLTB is used, Modem IIIa²

⁸ Tested to UL 8TH Edition

Table 1 (continued): C900V2 Compatible UL Listed Fire Alarm Control Panels (FACPs)

